



---

## Sheet (4)

1. A lossless resonant half-wavelength dipole antenna, with input impedance of 73 ohms, is connected to a transmission line whose characteristic impedance is 50 ohms. Assuming that the pattern of the antenna is given approximately by  $U = B_0 \sin^3 \theta$ . Find the maximum gain and maximum absolute gain of this antenna.
2. Calculate the directivity of an antenna with circular aperture of diameter 3 meter at frequency 5 GHz.
3. If the aperture efficiency of an antenna is 0.7 and the beam traveling at 6 GHz. Calculate the directivity, HPBW, and FNBW (approximately). Given circular aperture of diameter 3 meter.
4. What is the maximum effective aperture (approximately) for a beam antenna having HPBW of  $30^\circ$  &  $35^\circ$  in perpendicular planes intersecting in the beam axis? Minor lobes are small and may be neglected.
5. An antenna has a uniform field pattern for  $\theta$  between  $(45^\circ \& 90^\circ)$ ,  $\phi$  between  $(0^\circ \& 120^\circ)$ , if  $E = 3 \text{ V/m}$  at a distance of 500m from the antenna & Amplitude of current is 5A, find the radiation resistance of antenna, Directivity, and effective aperture?
6. An isotropic antenna has a field pattern given by  $E = 10 I_0 / r \text{ V/m}$ , where  $I_0$  is the maximum current,  $r$  is distance (m), find  $R_r$ . repeat for hemisphere antenna.
7. Find  $R_r$  of a unidirectional pattern of antenna with  $U = 8 \sin^2 \theta \sin^3 \phi \text{ wsr}^{-1}$ , where  $0 \leq \theta \leq \pi$  &  $0 \leq \phi \leq \pi$ . If  $I_{rms} = 3 \text{ A}$ .
8. What is the amplitude of current that would be required in a short dipole of length  $0.05\lambda$  to produce 100w of radiated power? Assume that the medium surrounding the short dipole in air and the current is uniform distribution.
9. What is the max? Power received at a distance of 0.5 Km. over a free-space 1GHz circuit consisting of a transmitting antenna with 25dB gain and receiving antenna with 20dB gain? The gain is with respect to a lossless isotropic source. The transmitting antenna input is 150W.



- 
10. A wave traveling normally outward from the page (toward the reader) is the resultant of two elliptically polarized waves, one with components of E given by:

$$\mathcal{E}'_y = 3 \cos \omega t$$

$$\mathcal{E}'_x = 7 \cos \left( \omega t + \frac{\pi}{2} \right)$$

And the other with components given by:

$$\mathcal{E}''_y = 2 \cos \omega t$$

$$\mathcal{E}''_x = 3 \cos \left( \omega t - \frac{\pi}{2} \right)$$

- (a) What is the axial ratio of the resultant wave?  
(b) Does the resultant vector E rotate clockwise or counterclockwise?
11. A wave traveling normally out of the page is resultant two elliptically polarized (EP) waves, one with components  $E_x = 5 \cos \omega t$  and  $E_y = 3 \sin \omega t$  and another with components  $E_r = 3e^{j\omega t}$  and  $E_L = 4e^{-j\omega t}$ . For the resultant wave, find (a) AR, and (b) the band of rotation and polarization.
12. A wave travelling normally out of page toward you is resultant of two linearly polarized component  $E_x = 3 \cos(\omega t)$  and  $E_y = 2 \cos(\omega t + 90)$  find the (i) axial ratio (ii) band of rotation (CW or CCW)

### REPORT

1. Design an antenna with omnidirectional amplitude pattern with a half-power beam width of  $90^\circ$ , Express its radiation intensity by  $U = \sin^n \theta$ . Determine the value of n and attempt to identify elements that exhibit such a pattern. Determine the directivity of the antenna.

*Good Luck*

Dr. Moataz Elsherbini  
Eng. Shaimaa Ezzat